

# 16 Port Ethernet Serial

## Ethernet to RS-232 Serial Server

Item # 4161

Easily communicate with up to 16 serial devices over an Ethernet network with the 4161 Ethernet serial server. Each RS-232 port implements all common modem control signals for maximum compatibility with a wide range of peripherals. SeaLINK products use industry standard RFC 2217 TCP/IP protocol for maximizing compatibility with the widest range of applications and devices.

Sealevel's SeaLINK software drivers and utilities make installation and operation easy using Windows 98SE, 2000, XP and Vista™ operating systems. After software installation, the 4161's serial ports appear as virtual COM ports to the host machine. Standard serial operating calls are transparently redirected to the 4161, guaranteeing compatibility with legacy serial devices and enabling backward compatibility with existing software. Serial tunneling is also supported, allowing two native serial devices to communicate over a network. Alternatively, raw data socket mode is supported, eliminating the need for a driver.

Housed in rugged 1U rackmount metal enclosures, 4161 devices are suitable for variety of applications and environments. Power indicator LEDs are included on both the front and rear of the enclosure, and each of the 16 RJ45 serial connectors provide both Tx and Rx LED indicators to assist in troubleshooting. Standard operating temperature range is 0-70° C, and extended temperature (-40° C - +85° C) models are available.

To simplify installation and configuration, a printed copy of the SeaLINK QuickStart Guide is included with all Ethernet serial server orders.



### Technical Specifications

Number of Ports	16
Max Data Rate	230.4K bps
Max Data Distance	50 feet
Power Requirement	9-30 VDC @ Min. 10W
Operating Temperature	0 - +70° C
Storage Temperature	-50° - +105° C
Humidity Range	10 - 90% R.H.
Dimensions	16.75 (W) x 1.5 (H) x 7.0 (D)

### Unique Features

- ▶ Ethernet 10/100BaseT (autosense)
- ▶ Appears as virtual COM ports to host machine
- ▶ Data rates to 230.4K bps
- ▶ Hot-swappable
- ▶ Built-in watchdog/reset circuit for fault tolerance
- ▶ Serial ports utilize RJ45 connectors
- ▶ 120V AC adapter included (12VDC @ 1A output, Item# TR117)
- ▶ Sealevel software supports Windows 98SE/2000/XP/Vista operating systems

# SEALEVEL

www.sealevel.com